

# Digital Volt Meter

<b>Digital Volt Meter</b>	
	
<b>Tool Type:</b> Electronics / measurement	
<b>Location:</b> Innovation Workshop	
<b>Description:</b> Digital voltmeter	
<b>Manufacturer:</b> Fluke	

## About

Measures AC voltage, DC voltage, AC current, DC current, capacitance, conductance, frequency, resistance, temperature (K)

## Detailed Specifications

- Max voltage measurement: 1000 V
- Basic AC voltage accuracy:  $\pm(0.7\% + 2)$
- Basic DC voltage accuracy:  $\pm0.05\% + 1$
- Max current measurement: 10 A
- Basic AC current accuracy:  $\pm(1.0\% + 2)$
- Basic DC current accuracy:  $\pm(0.2\% + 2)$
- Max resistance measurement: 50 M $\Omega$
- Resistance measurement accuracy:  $\pm0.2\%$
- Max capacitance measurement: 9999  $\mu$ F
- Min capacitance measurement: 10 pF
- Capacitance measurement accuracy:  $\pm(1\% + 2)$
- Max frequency measurement: 200 kHz
- Min frequency measurement: 0.5 Hz
- Frequency measurement accuracy:  $\pm(0.005\% + 1)$
- Max temperature measurement: 1,994 °F
- Min temperature measurement: -328 °F

# Reference Documentation

## Technical Data Sheet

From:  
<https://microfluidics.cnsi.ucsb.edu/wiki/> - Innovation Workshop Wiki

Permanent link:  
[https://microfluidics.cnsi.ucsb.edu/wiki/doku.php?id=digital\\_volt\\_meter&rev=1680905925](https://microfluidics.cnsi.ucsb.edu/wiki/doku.php?id=digital_volt_meter&rev=1680905925)

Last update: **2023/04/07 22:18**

